

Z-INFPR

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
-

Description

Return the print defaults of a cabinet.

When you do not specify the parameter Cabinet (i.e. if the only parameter you specify is Logical-printer-name), this subprogram returns the printer destination (TID or LU) for the printer and the associated printer profile.

When you specify the parameter Cabinet, this subprogram returns the print defaults for the cabinet.

Note:

When you specify both parameters, your specification for Logical-printer-name is ignored and the print defaults are returned.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2		X	
Cabinet	A8	R*		The name of the cabinet for which the print defaults are to be returned. If you want to return the printer destination (TID or LU), this parameter must be blank.
Logical-printer-name	A32	R*	X	The name of the printer.
TID/LU	A8		X	The printer destination for the specified printer. Only returned when Cabinet is blank.
Printer-profile	A32		X	The name of the printer profile to be used when an object is printed.
Formatting-profile	A32		X	The name of the profile to be used when a document is to be formatted.
Page-length	N4		X	The number of lines per page.
Page-width	N4		X	The number of characters per line.
Con-form	A1		X	If not marked, the user cannot use Con-form. In this case, the user cannot use the commands FORMAT and OUTPUT, and cannot ADD, DISPLAY or MODIFY a printer profile.
Print-banner	A1		X	If marked, the "Info" screen information is printed.
Print-notes	A1		X	If marked, attached notes, cover notes and enclosures are printed.
Print-address	A1		X	If marked, the addressee list of a mail item is printed.

Return Codes

00	Success
02	Invalid cabinet name
91	Printer association not found

Subprograms

None